

C2N-DB

Decorator Keypads

Crestron® C2N-DB Decorator Series keypads deliver simple, versatile pushbutton control for a broad range of residential and commercial applications. Clean, contemporary styling lends an attractive and unimposing appearance to any interior design, and affords convenient wall mount installation in perfect harmony with other Crestron devices as well as non-Crestron devices. They are offered in gloss white, almond, and black finishes, each formulated to match perfectly with popular off-the-shelf faceplates^[1].

Available in configurations of 6, 8, or 12 buttons, the Decorator keypads are designed for installation using standard electrical gang boxes and decorator-style faceplates^[1]. Multiple keypads can easily be ganged side-by-side along with other wall mount devices.

Custom engraving of the buttons is available to provide clear designation of each button's function. Every button is accompanied by an LED indicator, providing true status feedback for the most reliable operation. And, every button and LED is fully programmable for virtually any custom functionality, making C2N-DB Decorator Keypads perfect for controlling room lighting and shades, audio and video equipment, or any other application that demands simple, immediate one-touch control.

> Fits standard electrical gang boxes and decorator style faceplates

> New color-matched "gloss" finishes

> Available in 6, 8, and 12 button configurations

> Replaceable, custom-engravable button caps

> Programmable feedback LEDs

> Available in gloss almond, black, and white finishes

> Easy Cresnet® wiring

SPECIFICATIONS

Connectors

NET: (1) 4-pin 3.5mm detachable terminal block; Cresnet slave port, connects to Cresnet control network

Buttons

Keypad: (6, 8 or 12 depending upon model) replaceable engravable buttons, programmable

LED Indicators

Feedback: (1 per button) red LED, programmable and dimmable

Power Requirements

Cresnet Power Usage: 3 Watts (0.125 Amps @ 24 Volts DC)



Environmental

Temperature: 32° to 113°F (0° to 45°C)

Humidity: 10% to 90% RH (non-condensing)

Enclosure

1-gang mountable in a standard electrical box; Requires decorator style faceplate (not included)

Dimensions

(without faceplate)

Height: 4.16 in (106 mm)

Width: 1.79 in (46 mm)

Depth: 1.53 in (39 mm)

Weight

2.6 oz (75 g)

Available Models

C2N-DB6-A-S: Decorator Keypad, 6-Buttons, Almond, Gloss

C2N-DB6B: Decorator Keypad, 6-Buttons, Black, Gloss

C2N-DB6-W-S: Decorator Keypad, 6-Buttons, White, Gloss

C2N-DB8-A-S: Decorator Keypad, 8-Buttons, Almond, Gloss

C2N-DB8B: Decorator Keypad, 8-Buttons, Black, Gloss

C2N-DB8-W-S: Decorator Keypad, 8-Buttons, White, Gloss

C2N-DB12-A-S: Decorator Keypad, 12-Buttons, Almond, Gloss

C2N-DB12B: Decorator Keypad, 12-Buttons, Black, Gloss

C2N-DB12-W-S: Decorator Keypad, 12-Buttons, White, Gloss

Included Accessories

DB6-BTN-A-S Engravable Button Cap (blank) for C2N-DB6 and C2N-DB8, Almond, Gloss [Included Quantity for C2N-DB8-A-S: 4

[Included Quantity for C2N-DB6-A-S: 6]

DB6-BTNB Engravable Button Cap (blank) for C2N-DB6 and C2N-DB8, Black, Gloss [Included Quantity for C2N-DB8B: 4

[Included Quantity for C2N-DB6B: 6]

C2N-DB Decorator Keypads

DB6-BTN-W-S Engravable Button Cap (blank) for C2N-DB6 and C2N-DB8, White, Gloss [Included Quantity for C2N-DB8-W-S: 4
[Included Quantity for C2N-DB6-W-S: 6]

DB12-BTN-A-S Engravable Button Cap (blank) for C2N-DB12 and C2N-DB8, Almond, Gloss [Included Quantity for C2N-DB8-A-S: 4
[Included Quantity for C2N-DB12-A-S: 12]

DB12-BTNB Engravable Button Cap (blank) for C2N-DB12 and C2N-DB8, Black, Gloss [Included Quantity for C2N-DB8B: 4
[Included Quantity for C2N-DB12B: 12]

DB12-BTN-W-S Engravable Button Cap (blank) for C2N-DB12 and C2N-DB8, White, Gloss [Included Quantity for C2N-DB8-W-S: 4
[Included Quantity for C2N-DB12-W-S: 12]

Available Accessories

DB6-BTN-A-S: Engravable Button Cap for C2N-DB6 and C2N-DB8, Almond, Gloss

DB6-BTNB: Engravable Button Cap for C2N-DB6 and C2N-DB8, Black, Gloss

DB6-BTN-W-S: Engravable Button Cap for C2N-DB6 and C2N-DB8, White, Gloss

DB12-BTN-A-S: Engravable Button Cap for C2N-DB12 and C2N-DB8, Almond, Gloss

DB12-BTNB: Engravable Button Cap for C2N-DB12 and C2N-DB8, Black, Gloss

DB12-BTN-W-S: Engravable Button Cap for C2N-DB12 and C2N-DB8, White, Gloss

CRESNET-NP-TL-B250: Cresnet® Control Cable, non-plenum, teal, 250 ft box

CRESNET-NP-TL-B500: Cresnet® Control Cable, non-plenum, teal, 500 ft box

CRESNET-NP-TL-SP500: Cresnet® Control Cable, non-plenum, teal, 500 ft spool

CRESNET-NP-TL-SP1000: Cresnet® Control Cable, non-plenum, teal, 1000 ft spool

CRESNET-NP-BK-B500: Cresnet® Control Cable, non-plenum, black, 500 ft box

CRESNET-NP-OR-B500: Cresnet® Control Cable, non-plenum, orange, 500 ft box

CRESNET-NP-YL-B500: Cresnet® Control Cable, non-plenum, yellow, 500 ft box

CRESNET-P-TL-SP500: Cresnet® Control Cable, plenum, teal, 500 ft spool

CRESNET-P-TL-SP1000: Cresnet® Control Cable, plenum, teal, 1000 ft spool

CRESNET-P-BK-SP500: Cresnet® Control Cable, plenum, black, 500 ft spool

CRESNET-P-OR-SP500: Cresnet® Control Cable, plenum, orange, 500 ft spool

CRESNET-P-YL-SP500: Cresnet® Control Cable, plenum, yellow, 500 ft spool

CRESNET-HP-NP-TL-SP500: Cresnet® "High-Power" Control Cable, non-plenum, teal, 500 ft spool

CRESNET-HP-NP-TL-SP1000: Cresnet® "High-Power" Control Cable, non-plenum, teal, 1000 ft spool

CCR-L-1: Crestron® Color Ring

Notes:

1. Faceplate not included.

2. For C2N-DB8, use (4) DB6-BTN and (4) DB12-BTN.